

LIGHTHOUSE MAN



Subject: Beacon alteration to fit on a Fan Junction Box.

As our web site states our beacon 01, Liteman, and Deluxe beacons must be altered just a little for it to fit inside the top housing of our Deluxe Stucco and our E-Line Stucco lighthouses. There is just a simple 2 step process to alter your beacon.



Step #1

First please take a pair of pliers and remove the tabs or the ears of the base plate that the beacon is assembled on. You can simply bend the tabs up and down 2-3 times and the tabs will snap off.



Step #2 Now please place the beacon on the fan junction box with the motor in the front left hand corner of the box. Next step is line up the beacon base plate with the junction box threaded tabs. Take a marker and mark the base plate. Now simply drill a 1/4" hole in the beacon base plate. Now attach the beacon to the base plate and the alteration is completed.

